

VibTrans-R

Extend the Life of Rotating Equipment





VibTrans-R

The VibTrans-R 19" Vibration Monitoring Rack, is the latest technology for maintaining safety in large industrial rotating machines.

VibTrans-R is a simple, machinery protection system, a cost effective solution to protect machines by giving online information which enables connect with the PLC or DCS of a plant and to take a shut down whenever required through proper planning.

It is a perfect solution to keep your machine running.

VibTrans-R is the right size, right price, right quality product with all the features for vibration monitoring needs.

Why do we need vibration monitoring?

Rotating machinery is the heart of any plant. It is very essential to run a machine at high efficiency without any trouble. The deterioration in the efficiency of rotating machines cannot be predicted, but with the help of the online Vibration Monitoring and Analysis System, this can be properly judged. Vibration monitoring is the easiest way to keep machines healthy and efficient in the long run. This reduces the overall operating cost as well as the down time period, increases plant availability and efficiency of rotating machines. To cope with global competition and pressure, every plant wishes a maximum uptime, hence maintenance planners are moving from active maintenance to proactive maintenance.

Traditionally, plant maintenance was performed based on the Time Based Maintenance system (TBM), i.e. preventive maintenance. A schedule was set up on the basis of OEM manuals or time-based on MTBF (Mean time between failures) or past failure inputs were used for data analysis. However, the life of the machine can be extended, if online monitoring is done in a cost effective way.

Features

Microprocessor based digital vibration monitoring system

Vibration monitoring system in a 19" rack

API-670 compliant

Redundant and hot swappable functionality for all types of modules

Field selectable filters

Communication with DCS and HMI via MODBUS - RS 485 and ethernet

4-20 mA and 02 relay outputs per channel

Common configuration port for all modules

Phase marker connectivity with RPM measurement

Options

Connection to analysis software with the help of APU

Continuous online monitoring of rotating assets on mobiles through

Vibrosense M

Remote vibration monitoring

Benefits

Improve plant maintenance and profit


Enhance safety of machines and people


Increase the life span of machines

Reduce inventory cost

Reduce manpower cost to get data at regular intervals

Reduce energy cost





VibTrans-R Hardware

VibTrans-R Instrument Rack Enclosure

The VibTrans R rack is a 19" rack

Maximum no. of mountable modules:

AV modules - upto 21 (can accommodate upto 42 vibration (acceleration/velocity) 21 x 2 channel cards)

PM module - Up 8 (can accommodate upto 8

Phase marker (non contact type) 4 x 2 channel cards)

Power supply modules - 2

Communication module - 2



VibTrans-R-PS

Power supply module

VibTrans-R-PS-230: 84V-264V AC at 50-60 Hz

VibTrans-R-PS-24: 18-36V DC VibTrans-R-PS-110: 60-160V DC

Two power supply modules in any combination can be mounted on a rack for power supply redundancy.



VibTrans-R-CM

Communication module

Transmits data from the back communication port to a local display unit and also communicates with a service PC/laptop via front USB port for configuration of vibration monitor.

It also communicates data between VibTrans-R rack and DCS or PLC

Redundant communication with PLC/DCS



VibTrans-R-PM

Phase marker module

Accepts upto 8 phase marker sensors and buffer output is available on rear terminals and buffer / pulse on front BNC

Speed measurement is also possible



VibTrans-R-AV

Vibration monitor module

Accepts vibration parameters for casing vibrations with accelerometer or velocity sensor input upto 2 channels/module

There are 02 relays per channel for alert and danger Each monitor has recorder output (4-20mADC) and buffer output available on rear terminals and on front BNC



Software

RC (Rack configuration software)

RC software displays measured values, monitoring status and the configuration of each module.



Technical Specifications

Parameters measured by Vibration Input Module	Velocity		
	Mode	:	Peak Or RMS value
	Units	:	mm/sec or in/sec
	Range	:	Please refer ordering information in data sheet
	Displacement		
	Mode	:	Peak or RMS or Peak - Peak
	Units	:	Microns or mils
	Range	:	Please refer ordering information in data sheet
	Output	:	4-20 mA DC for each channel
	Through rear panel terminals	:	Buffered output for Ch1 and Ch2 on
			rear terminals and on front BNC
	Relay output	:	Number of relay: 2/ Channel for alert and
			danger
		:	Contact type : Dry contact (SPDT)
			Contact capacity: 230VAC / 5A, 30VDC / 5A
	I/O conversion accuracy		±1% of F.S. at 25°C
			±2% of F.S. at 0°C to 65°C
	Sensor failure	:	On display, Modbus
Input Sensors	Accelerometer	:	100mv/g (+/- 10%)
Options	Velocity Sensor	:	4 mv/mm/sec (+/- 10%)
	Communication Redundancy		Modbus / TCP and Modbus / RTU (half duplex and
			full duplex)
			Communication items for data transmission:
Communication Module			Measurement value, measurement mode with unit,
			Danger alarm status, Alert alarm status,
			OK alarm status, danger bypass status, Power OK status
	Voltage	_	
Power Supply Module Redundant	voitage	•	VibTrans R RS 24 : 18V 26VDC
			VibTrans-R-PS-24 : 18V-36VDC
	On and the second little		VibTrans-R-PS-110 : 60V-160VDC
	Operating conditions		0.4.0500
	Temperature range	:	0 to 65°C upto 95% humidity (non condensing)
Mounting and Dimensional Detail	Panel mounted	:	Size: 480.3 X 281 X 276.3 mm (W X H X D)

System Architecture Control Room Buffer output Local Display in Panel (BNC on front panel and terminals at the back) Analog output 4-20mA each channel 2 Relay outputs each channel Modbus output VMS Panel **Field** Field Field Field JB JB JB Input from transducers (Contact type piezo velocity sensors or accelerometers / non contact type eddy current phase marker sensors) 10m extension cable with SS conduit from sensor to field JB Pump coupled with motor Fan coupled with motor CT fan HT motors Vertical pump

Applications



Power

Induced draft fans
Forced draft fans
Primary air fans
Coal mills
Coal crushers
Condensate extraction pump
Cooling water pump
Boiler feed pump
Auxillary cooling water pump
Raw water pump
Make up water pump



Steel

Fans and blowers HT motors Gear boxes Utility area - various HT Motors and pumps



Cement

and pumps

Fans
Crushers
Kiln
Vertical raw mill
Ball mill
Motors
Gear boxes
Utility area - various HT motors



Infrastructure

Fans
Blowers in various IT malls
Shopping complexes
Water treatment and lift
Irrigation pumps



Paper

Pumps Motors Gear boxes Paper rollers Paper machines



Dairy / Food / Beverages

Mixers
Centrifuges
Pumps
Motors
Air compressors
Fans
Conveyors



Textile

Pumps
Fans and motors
Utility area - various HT
Motors and gear boxes



Mining

Pumps Crushers Conveyors Motors Gear boxes




Pharma

Fans and motors assembly in Air handling units Centrifuges Conveyors

Mountable Module Slot Number

Module Description	Module Part Number	Slot Number												
·		U1	U2	U3(Nil)	U4	U5	U6	U7	U8	U9	U10	U11	U12	U13
		L1	L2	L3	L4	L5	L6	L7	L8	L9	L10	L11	L12	L13
Power supply module 230 VAC	VibTrans-R-PS-230	•												
Power supply module 110 VDC	VibTrans-R-PS-110	•												
Power supply module 24 VDC	VibTrans-R-PS-24	•												
Dual channel Accleration / Velocity (AV) Monitor	VibTrans-R-AV			• *	•	•	•	•	•	•	•	•	•	•
Dual channel phase (PM) monitor	VibTrans-R-PM			•	•	• **								
Communication (CM) monitor TCP/IP, RTU, Modbus	VibTrans-R-CM		•											
Face Plate for PS	VibTrans-R-FP-12T	•												
Face Plate for PM/AV/CM	VibTrans-R-FP-6T		•	•	•	•	•	•	•	•	•	•	•	•





Forbes Marshall Krohne Marshall Forbes Marshall Arca Codel International Forbes Solar Forbes Vyncke Forbes Marshall Steam Systems Opp 106th Milestone Bombay Poona Road Kasarwadi, Pune - 411 034. INDIA Tel: 91(0)20-27145595, 39858555 Fax: 91(0)20-27147413 B-85, Phase II, Chakan Indl Area Sawardari, Chakan, Tal. Khed Dist. Pune - 410 501. INDIA Tel: 91(0)2135-393400 A-34/35, MIDC H Block Pimpri, Pune - 411 018. INDIA. Tel: 91(0)20-27442020, 39851199 Fax: 91(0)20-27442040

CIN No.: U28996PN1985PTC037806 www.forbesmarshall.com

Email: mvyas@forbesmarshall.com, ccmidc@forbesmarshall.com

© All rights reserved. Any reproduction or distribution in part or as a whole without written permission of Forbes Marshall Pvt Ltd, its associate companies or its subsidiaries ("FM Group") is prohibited.

Information, designs or specifications in this document are subject to change without notice. Responsibility for suitability, selection, installation, use, operation or maintenance of the product(s) rests solely with the purchaser and/or user. The contents of this document are presented for informational purposes only. FM Group disclaims liabilities or losses that may be incurred as a consequence of the use of this information.